## **Patriot Energizer Comparison** & Selection Chart

Patriot. DATAMARS

DATAMARS Livestock.

MODEL	POWER	COVERAGE AREA	CONTAINMENT OR EXCLUSION	OUTPUT ENERGY (UP TO)	STORED ENERGY (UP TO)	OUTPUT VOLTAGE (UP TO)	INTERNAL RECHARGEABLE BATTERY	CURRENT CONSUMPTION	SOLAR PANEL
PMX1500	-	600 ACRES / 200 MILES	ही हो तो करते तो में के प्रज	12 J	20 J	10.6kV max, 8.4kV @ 500 Ω			
PMX600	-	300 ACRES / 100 MILES	ही को ही तो करते तो भे से भ र	6.7 J	9.9 J	10.2kV max, 7kV @ 500 Ω			
PMX350	-	200 ACRES / 65 MILES	रि मा ली तो का ती तो म से भ र	3.5 J	6.4 J	10.2kV max, 6.2kV @ 500 Ω			
P30		200 ACRES / 65 MILES	ही मा लो तो का तो भी से भाष	3 J	4.5 J	11kV max, 6.4 kV @ 500 Ω		300mA	30 watt
SG3500 <b>NEW</b> *		200 ACRES / 65 MILES	ही को तो का तो भ से भ र	3.5 J	4.6 J	10.1kV max, 9.2kV @ 2,000 Ω	12V; 24Ah	<290mA	INTEGRATED
SG2000 NEW*		165 ACRES / 50 MILES	ही मां लो तो का तो भ से भ र	2 J	2.6J	10.5kV max, 9kV @ 2,000 Ω	12V; 12Ah	<170mA	INTEGRATED
P20		165 ACRES / 50 MILES	ही मा लो तो का लो तो भ से भ र	2 J	2.7 J	10.5kVmax, 6kV @ 500 Ω		170mA	20 watt
PBX200		165 ACRES / 50 MILES	👥 ला तो तो का तो भी से भाष	1.9 J	2.7 J	10.4kV max, 5.8kV @ 500 Ω		170mA	20 watt
PMX200	-	165 ACRES / 50 MILES	रि ला ली तो का ली तो भ से भ र	2 J	31	9.5kV max, 5.7kV @ 500 Ω			
P10		100 ACRES / 30 MILES	ही लो तो का तो भ से भ र	1 J	1.4 J	9.7kV max, 5.4kV @ 500 Ω		90mA	10 watt
PBX120		100 ACRES / 30 MILES	रि मा ली तो का ली तो में के प्रभ	1.2 J	1.7 J	10kV max, 5.5kV @ 500 Ω		110mA	10 watt
PMX120	-	100 ACRES / 30 MILES	👥 ला तो तो का तो भी से भ र	1.2 J	1.7 J	10.2kV max, 5.5kV @ 500 Ω			
SG1000		140 ACRES / 40 MILES	死 ला तो तो का तो भी से भ र	1 J	1.3 J	9.6kV max, 7kV @ 1,000 Ω	12V; 7Ah	90mA	INTEGRATED
SG500	->` •	100 ACRES / 30 MILES	रि ला तो तो का तो भी से भाष	0.5 J	0.65 J	9.8kV max, 6.2kV @ 1,000 Ω	12V; 7Ah	50mA	INTEGRATED
Р5		60 ACRES / 15 MILES	रि ला ती तो करते तो भे से भ र	0.5 J	0.7 J	8kV max, 4.5kV @ 500 Ω		45mA	10 watt
PBX50		60 ACRES / 15 MILES	死 ला तो तो का तो भी से भ र	0.5 J	0.67 J	8.2kV max, 4.4kV @ 500 Ω		50mA	10 watt
PMX50	-	60 ACRES / 15 MILES	रि ला तो तो का तो भी से भ र	0.5 J	0.85 J	10kV max, 4.8kV @ 500 Ω			
PB12	<b></b> ,	40 ACRES / 10 MILES	m n H d u d	0.12 J	0.16 J	8kV max, 4.5kV @ 500 Ω		7-25mA	
PE10B	·	40 ACRES / 10 MILES	m n H d u d	0.3 J	0.49 J	5kV max, 3.5kV @ 500 Ω		36mA	
PE10	-	40 ACRES / 10 MILES	m n H d a d	0.3 J	0.49 J	5kV max, 3.5kV @ 500 Ω			
SG150	->`	40 ACRES / 10 MILES	m n h d e d	0.15 J	0.21 J	9.3kV max, 4.1kV @ 1,000 Ω	6V; 4Ah	30mA	
PE5B	<b>•</b>	20 ACRES / 5 MILES	m n H d e d	0.2 J	0.3 J	5kV max, 3.2kV @ 500 Ω		24mA	
PE5	-	20 ACRES / 5 MILES	m n h d e d	0.2 J	0.32 J	5kV max, 3.2kV @ 500 Ω			
SG80		15 ACRES / 3 MILES	m n H d u d	0.08 J	0.10 J	7.3kV max, 3.2kV @ 1,000 Ω	6V; 4Ah	16mA	
PE2	-	8 ACRES / 2 MILES	Hated	0.1 J	0.16 J	5kV max, 2.8kV @ 500 Ω			
PS5		8 ACRES / 2 MILES	H & & Y	0.04 J	0.06 J	7.4kV max, 2.6kV @ 1,000 Ω	4V		

Table represents typical values. \* NOTE: Range claims are a general guide and based on single-wire, weed-free fences. Actual range claims depend on many factors including fence and operation conditions, livestock type, and environment. Solar panel wattage numbers are general recommendations and may vary based on geography. Please consult your local electric fence professional to determine the best solar panel for you. All Patriot energizers are low-impedance.